

Microphone connection for danita CB units

Mobile	Mic. connector pins						Pin row
	Pin 1	Pin 2	Pin 3	Pin 4	Pin 5	Pin 6	
4 pin connector	GND	Mic.	TX	RX			1.2.3.4
5 pin connector	Mic.	GND	TX		RX		1.4.2.5.3
6 pin connector	Mic.	RX	TX	Ch. SW*1	GND		1.2.3.4.5.centre 6 (d.3000)
6 pin connector	Mic.	RX	TX	Ch. SW*2	GND		1.2.3.4.5.c6 d.3000Multi

*1 Channel switch to + DC. d.3000 standard

*2 Channel switch to - GND. d.3000Multi

Org. mic. colour							Models
4 pin	Shield	White	Red	Black			d.240,1240
4 pin	Shield	Yellow	White	Red			d.640, d2000Multi
5 pin	White	Shield	Red		Black		d.440,1540
6 pin	White	Blue	Red	Black	Shield		d.3000
6 pin	Yellow	Blue	Red	Purple	Black	White	d.3000 Multi

Spare microphones. w/connector							For Models
461 6pin Multi	Yellow	Blue	Red	Purple	Black	White	d.3000Multi
460 6pin St mic	White	Blue	Red	Black	Shield		d.3000
451 6pin St. mic.	White	Red	Brown	Black	Shield	Blue	d.1608
452 4pin St. mic.	Shield	Yellow	White	Red			d.240, 1240, 640, 2000M
454 5pin St. mic.	White	Shield	Red		Black		d.440, 1540

Spare mic. w/o connector.

Mic. / Function	GND	Mic.	TX	RX	GND	Ext.power	
453 d.408	Shield	Yellow	White	Red	Black		331548
MB4 Zetagi	Shield	White	Red	Blue		Yellow	
KM-9900	Shield	White	Red	Blue	Black		

(All colour may be changed without prior notice. (All colour noted February 1999))

Handheld	danita 608	danita 301
Mic. jack 2,5mm	< 2K Ohm	
SP jack 3,5mm	=> 8 Ohm	
CHG jack 1,3mm	- in centre, 50/100 mA	+ in centre, 12 Volt
Power jack 1,3mm	+ in centre, 12 Volt (CHG)	+ in centre, 12 Volt